

LT87121 --- Product Brief

eDPx to eDP/DP Converter

Features

● eDPx Receiver

- 1/2/4/8 configurable data lanes
- Input data rate is up to 3.75Gbps
- Adaptive receiver equalization for PCB and cable losses
- Support 3-byte,4-byte,5-byte mode
- Support 6bit,8bit,10bit color depth
- Support 2 sections,4 sections input mode
- Support Center Spread Spectrum , 30kHz/5000ppm

● eDP/DP Transmitter

- Compliant with VESA eDP1.4/DP 1.2
- Support 1.62/2.7/5.4 Gbps per lane
- Support 1/2/4 lanes
- Support SSC
- Programmable transmitter swing and pre-emphasis
- 1Mbps AUX channel
- MCCS Over AUX Support
- Support ASSR
- Support video formats: 6bpc RGB, 8bpc RGB/YCbCr 422/YCbCr 444, 10bpc RGB/YCbCr422/YCbCr 444

● Miscellaneous

- Internal or external oscillator

- Integrated microprocessor
- Embedded SPI flash for firmware
- Integrated 100/400kHz I2C slave
- Firmware update through SPI or I2C interface
- IIS/SPDIF input support(transmitter is DP mode)
- CSC support
- Dither support
- UART Support
- Backlight Control Support(transmitter is eDP mode)
- Low power consumption
- Power supply: 3.3V for I/O and 1.2V for core
- Temperature Range: -40°C ~ +85°C
- 64 pin QFN 7.5*7.5 package

Description

The LT87121 is a high performance eDPx to eDp/DP converter, designed to connect eDPx source to an eDP/DP sink.

The device is capable of automatic operation which is enabled by an integrated microprocessor that uses an embedded SPI flash for firmware storage. System control is also available through the use of a dedicated configuration I2C slave interface.

Applications



Figure 1. Application Diagram

Ordering Information

Table 1. Ordering Information

Part Number	Operating Temperature Range	Package	Packing Method
LT87121	-40° C to +85° C	QFN64 (7.5*7.5)	Tray

Copyright © 2019 Lontium Semiconductor Corporation, All rights reserved.

Lontium Semiconductor Proprietary & Confidential

This document and the information it contains belong to Lontium Semiconductor. Any review, use, dissemination, distribution or copying of this document or its information outside the scope of a signed agreement with Lontium is strictly prohibited.

LONTIUM DISCLAIMS ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING THOSE OF NONINFRINGEMENT, MERCHANTABILITY, TITLE AND FITNESS FOR A PARTICULAR PURPOSE. CUSTOMERS EXPRESSLY ASSUME THEIR OWN RISK IN RELYING ON THIS DOCUMENT.

LONTIUM PRODUCTS ARE NOT DESIGNED OR INTENDED FOR USE IN LIFE SUPPORT APPLIANCES, DEVICES OR SYSTEMS WHERE A MALFUNCTION OF A LONTIUM DEVICE COULD RESULT IN A PERSONAL INJURY OR LOSS OF LIFE.

Lontium assumes no responsibility for any errors in this document, and makes no commitment to update the information contained herein. Lontium reserves the right to change or discontinue this document and the products it describes at any time, without notice. Other than as set forth in a separate, signed, written agreement, Lontium grants the user of this document no right, title or interest in the document, the information it contains or the intellectual property in embodies.

Trademarks

Lontium™ 龙迅™ and ClearEdge™ is a registered trademark of Lontium Semiconductor. All other brand names, product names, trademarks, and registered trademarks contained herein are the property of their respective owners.

Visit our corporate web page at: www.lontiumsemi.com

Technical support: support@lontium.com

Sales: sales@lontium.com